


Getting to know your telephone

You have an **ALCATEL 4023 REFLEXES** digital telephone. The alphabetic keypad, the screen and the icons will help you use your telephone easily and make optimum use of the many functions offered.

Display and display keys

Comprises two lines and several pages of information concerning the present call and the functions accessible using the keys corresponding to the lines on the screen.

Light indicating voice messages received.



Installing the programmable key label

A printed label is supplied with the terminal. This should be installed beneath the programmable keys.

- Lift the lower part of the terminal.
- Lift the keypad cover.
- Slide your printed label into position.
- Replace the cover inserting the top first, then press down the lower part of the terminal.



Programmable keys and icons

To make a call, activate a service or manage your calls. Each key has a corresponding icon:

Line icons

- Incoming call (flashing).
- Call in progress.
- Call on hold.
- Call on common hold.

Function icons

- Function active.
- Function requiring action.
- Terminal or line busy.

Access the various mail services

- Divert your calls to another terminal.
- Access the various mail services.
- Access your personal directory.
- ISDN: Call an ISDN correspondent.
- Transfer call to another terminal.
- Activate the "Call by name" function.

Audio keys

- Loudspeaker: to share a conversation.
- To reduce loudspeaker or receiver volume.
- To increase loudspeaker or receiver volume.
- Mute, so your correspondent cannot hear you.
- Hands free: to make or answer a call without lifting the receiver.

To check or modify your key programming.

To end a call or programming.

Alphabetic keypad

The keypad is protected by a flap and can be used for the call by name, the message service and programming. Open by pressing the top.

UNDERSTANDING YOUR TELEPHONE

Alphabetic keypad for call by name



Type the name of your correspondent: a name is displayed, with the corresponding order number in a list.

The following display keys are proposed:



Next

display next name in list



Prev

display previous name in list



Send

to call when name is OK

SETTING UP

Adjusting screen or icon brightness



Custom

Contrast

Screen

Icon

select the required level by consecutive presses



Ok



consecutive presses to select tune (8)

Selecting ringer tune and adjusting volume



Custom

Meloda

Meloda

Level+

consecutive presses to select tune (8)



Ok



consecutive presses to adjust volume (7)

Selecting a language



Custom

Lang

English

Choice

present language



Ok



consecutive presses

Locking/unlocking your telephone



lock



personal code (4 digits) Default code 1515

to lock



Yes



No

to unlock

MAKING A CALL

To make a call



lift the receiver



hands free



press a line key



dial the number for your call

To answer



lift the receiver



hands free



hang-up

To terminate a conversation



hang-up



to end a call

Making an outside call



key for outside line



dial 9



dial the number for your call



number dialled

Making an internal call



key for internal line



number required



operator



name of person called or operator

Calling from the directory

Personal directory



Helen

press one of the keys 0 to 9

Common directory



to call by name



directory number (7000 to 7399)

Redialling



number stored



redial



number called

Storing number or being called back



your correspondent does not reply



NbSave



NbBack



to end a call

ALCATEL OFFICE*

Table of codes

A function is activated by entering the corresponding code on the keypad.

Function	Default code	Your code	Function	Default code	Your code
Answer general bell	15		Hunting group out	66	
Answer paging	49		Immediate diversion	61	
Appointment time (programmed)			Infrude on a call	7 or A	
Automatic callback if terminal busy	19 or #		Line allocation		
Broadcast groups	41 to 48		Line allocation + callback with charge info.		
Broker call	2		Meter Total Recall	17	
Business account code			Moving a terminal	748	
Calibrated break	66		Open door		
Cancel all diversions	60		Operator call	0	
Cancel automatic callback	19		Paging	40	
Cancel enquiry call	3		Park / retrieve parked call	12	
Cancel follow me	69		Protect a call	89	
Common directory numbers	7000 to 7399		Redial last number	40	
Conference	50		Replacing a terminal	747	
Consult voice messages			Seize main line	9	
Consultation of call on hold	14		Seize secondary lines	82 to 88	
Divert group calls	65		Selective diversion		
Divert if busy	62		Substitution (business charge code)		
Divert to paging	64		Switch to programming	800	
Do not disturb	63		Terminal call	200	
DTMF End to End	69 or D		to 399		
Follow me diversion	68		Terminal call pick-up	13	
Group call	51 to 58		Text message (call back later)	50	
Group call pick-up	14		Voice message (codes reserved)	806	
Hunting group in	67		and 807		

Your telephone provides access to a number of functions, depending on your system version and configuration.

You can programme keys as required and print new labels. See the installation guide or contact your distributor.

Name: Telephone No:

Fax No: Mobile No:

E-mail address:

Alcatel Business Systems reserves the right to modify without notice the characteristics of its products in order the interest of its customers.

Alcatel Business Systems - 56, avenue Jean-Jaurès - 92707 Colombes Cedex R.C. Paris 602 033 185

HANDLING SEVERAL CALLS

Calling a second person during a conversation

During a conversation, to call a second person.



Receiving a second call

During a conversation, another person is trying to call you.



Transferring a call

During a conversation, to transfer the call to another number.



Switching between two calls (Broker call)

During a conversation, another call is on hold. To accept the second call:



Three-way conference

During a conversation, a second call is on hold.



CUSTOMISING YOUR TELEPHONE

Programming your personal code


The default code for your telephone is 1515.



Modifying value corresponding to key



Programming your personal directory



GROUP OPERATION

Call pick-up

- Another telephone is ringing
- A telephone in your group is ringing



Monitoring calls to other terminals



Answering a general bell

If the operator is absent, to answer incoming calls to the operator.




Calling a correspondent on his loudspeaker

If you have authorisation, you can remotely activate his loudspeaker.




Filtering incoming calls



Sending a written message to your correspondents

Internal number



Making an ISDN call



WHILE YOU ARE AWAY - WHEN YOU RETURN

Diverting calls to another number



Diverting calls to a recorded message (option)



Follow me diversion

From terminal to receive the diverted calls.



Cancelling all diversions



Consulting recorded messages

The light indicates that messages have been received.

Written messages



display number of messages received



Voice messages (option)

